

Technical Details		6 -7.5 - 10 KVA	شرکت توانیرو
POWER	Rated Power	6 - 7.5 - 10 (KVA)	
GENERAL DATA	Topology	Lineinteractive , double conversion / inverter	
	Efficiency	Up to 85%	
	Control	Analog - Digital	
INPUT	Voltage	220 One phase 380 VAC Three phase	
	Voltage Range	± 25%	
	Frequency	50 Hz	
	Frequency Range	± 5%	
	THDi	≤ 4%	
OUTPUT	Voltage	220 VAC	
	Frequency	50 Hz	
	Power Factor	0.8	
	THDv	≤ 3% (Linear load) , ≤ 5% (non-linear load)	
	Over load	125% rated load for 60 sec , 150% rated load for 30 sec .	
BATTERY	Battery Type	Maintenance-free sealed lead acid battery (12 V)	
	Charging Current	6 - 7.5 KVA = 8A , 10 KVA = 10 A	

آدرس : تهران ، خیابان کارگر جنوبی ، نرسیده به میدان انقلاب ، خیابان شهید وحید نظری کوی شایان ، پلاک ۱

تلفکس : ۶۶۴-۲۸۴۴ - ۶۶۴-۵۵۹۳